

## Data sheet

### FM 050 - Counter module (050-1BB00)

#### Technical data

<b>Order no.</b>	<b>050-1BB00</b>
Type	FM 050 - Counter module
Module ID	08C3 380A
<b>General information</b>	
Note	-
Features	2x Counter 32 Bit (AB), DC 24 V Up to 400 kHz
<b>Current consumption/power loss</b>	
Current consumption from backplane bus	75 mA
Power loss	0.9 W
<b>Technical data digital inputs</b>	
Number of inputs	4
Cable length, shielded	100 m
Cable length, unshielded	-
Rated load voltage	DC 20.4...28.8 V
Reverse polarity protection of rated load voltage	-
Current consumption from load voltage L+ (without load)	15 mA
Rated value	DC 20.4...28.8 V
Permitted range	-
Input voltage for signal "0"	DC 0...5 V
Input voltage for signal "1"	DC 15...28.8 V
Input voltage hysteresis	-
Signal logic input	-
Frequency range	-
Input resistance	-
Input current for signal "1"	3 mA
Connection of Two-Wire-BEROs possible	yes
Max. permissible BERO quiescent current	0.5 mA
Input delay of "0" to "1"	0.8 µs
Input delay of "1" to "0"	0.8 µs
Number of simultaneously utilizable inputs horizontal configuration	4
Number of simultaneously utilizable inputs vertical configuration	4
Input characteristic curve	IEC 61131-2, type 1
Initial data size	12 Byte
<b>Technical data digital outputs</b>	
Number of outputs	-
Cable length, shielded	-
Cable length, unshielded	-
Rated load voltage	-
Permitted range	-
Current consumption from load voltage L+ (without load)	-
Output current at signal "1", rated value	-

Signal logic output	-
Output delay of "0" to "1"	-
Output delay of "1" to "0"	-
Minimum load current	-
Lamp load	-
Parallel switching of outputs for redundant control of a load	-
Parallel switching of outputs for increased power	-
Actuation of digital input	-
Switching frequency with resistive load	-
Switching frequency with inductive load	-
Switching frequency on lamp load	-
Internal limitation of inductive shut-off voltage	-
Short-circuit protection of output	-
Trigger level	-
Number of operating cycle of relay outputs	-
Switching capacity of contacts	-
Output data size	12 Byte

## Technical data counters

Number of counters	2
Cable length, shielded	-
Cable length, unshielded	-
Counter width	32 Bit
Number of inputs	-
Input signals	-
Termination resistance (RS422)	-
Maximum input frequency	100 kHz
Maximum input frequency (TTL)	-
Maximum input frequency (RS422)	-
Maximum count frequency	400 kHz
Maximum count frequency (TTL)	-
Maximum count frequency (RS422)	-
Encoder supply (output)	-
Mode incremental encoder	yes
Mode pulse / direction	yes
Mode forwards/backwards	-
Mode pulse	-
Mode frequency counter	-
Mode period measurement	-
Gate input available	-
Latch input available	-
Reset input available	-
Counter output available	-

## Status information, alarms, diagnostics

Status display	yes
Interrupts	yes, parameterizable
Process alarm	yes, parameterizable
Diagnostic interrupt	yes, parameterizable
Diagnostic functions	yes, parameterizable

Diagnostics information read-out	possible
Module state	green LED
Module error display	red LED
Channel error display	none

## Isolation

Between channels	-
Between channels of groups to	-
Between channels and backplane bus	yes
Between channels and power supply	-
Max. potential difference between circuits	-
Max. potential difference between inputs (Ucm)	-
Max. potential difference between Mana and Mintern (Uiso)	-
Max. potential difference between inputs and Mana (Ucm)	-
Max. potential difference between inputs and Mintern (Uiso)	-
Max. potential difference between Mintern and outputs	-
Insulation tested with	DC 500 V

## Datasizes

Input bytes	12
Output bytes	12
Parameter bytes	45
Diagnostic bytes	20

## Housing

Material	PPE / PPE GF10
Mounting	Profile rail 35 mm

## Mechanical data

Dimensions (WxHxD)	12.9 mm x 109 mm x 76.5 mm
Net weight	58 g
Weight including accessories	58 g
Gross weight	73 g

## Environmental conditions

Operating temperature	0 °C to 60 °C
Storage temperature	-25 °C to 70 °C

## Certifications

UL certification	yes
KC certification	yes
UKCA certification	yes
ChinaRoHS certification	yes